

Tabella 6.A - Cavi unipolari senza guaina in PVC posati in tubo o in canale (Tipi di posa di cui alla tab. 2.A)

Sezione [mm ²]	Numero cond. cavi	PORTATA (A)																			
		Numero di circuiti																			
		1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1,5	2	17,5	14	12,5	11,5	10,5	10	9,5	9	9	8,5	8	8	7,5	7,5	7,5	7	7	7	7	6,5
	3	15,5	12,5	11	10	9,5	9	8,5	8	8	7,5	7,5	7	7	6,5	6,5	6,5	6	6	6	6
2,5	2	24	19	17	15,5	14,5	13,5	13	12,5	12	11,5	11,5	11	10,5	10,5	10	10	9,5	9,5	9,5	9
	3	21	17	14,5	13,5	12,5	12	11,5	11	10,5	10	10	9,5	9	9	8,5	8,5	8,5	8	8	8
4	2	32	26	22	21	19	18	17,5	16,5	16	15,5	15	14,5	14	14	13,5	13	13	13	12,5	12
	3	28	22	19,5	18	17	16	15	14,5	14	13,5	13	12,5	12,5	12	11,5	11	11	11	11	10,5
6	2	41	33	29	27	25	23	22	21	21	19,5	19,5	18,5	18	17,5	17	17	16,5	16,5	16	15,5
	3	36	29	25	23	22	21	19,5	18,5	18	17,5	17	16	16	15,5	15	15	14,5	14,5	14	13,5
10	2	57	46	40	37	34	32	31	30	29	27	27	26	25	25	24	23	23	23	22	22
	3	50	40	35	33	30	29	27	26	25	24	24	23	22	22	21	21	20	20	19,5	19
16	2	76	61	53	49	46	43	41	40	39	36	36	34	33	33	32	31	30	30	30	29
	3	68	54	48	44	41	39	37	35	34	33	32	31	30	29	28	27	27	27	26	26
25	2	101	81	71	66	61	58	55	53	51	48	47	45	44	43	42	41	40	40	39	38
	3	89	71	62	58	53	51	48	46	45	43	42	40	39	38	37	36	36	36	35	34
35	2	125	100	88	81	75	71	68	65	63	60	59	56	55	54	53	51	50	50	49	48
	3	110	88	77	72	66	63	59	57	55	53	52	50	48	47	46	45	44	44	43	42
50	2	151	121	106	98	91	86	82	79	76	72	71	68	66	65	63	62	60	60	59	57
	3	134	107	94	87	80	76	72	70	67	64	63	61	59	58	56	55	54	54	52	51
70	2	192	154	134	125	115	109	104	100	96	92	90	86	84	83	81	79	77	77	75	73
	3	171	137	120	111	103	97	92	89	86	82	80	77	75	74	72	70	68	68	67	65
95	2	232	186	162	151	139	132	125	121	116	111	109	104	102	100	97	95	93	93	90	88
	3	207	166	145	135	124	118	112	108	104	99	97	93	91	89	87	85	83	83	81	79
120	2	269	215	189	175	161	153	145	140	135	129	126	121	118	116	113	110	108	108	105	102
	3	239	191	167	155	143	136	129	124	120	115	112	108	105	103	100	98	96	96	93	91
150	2	309	247	216	201	185	176	167	161	155	148	145	139	136	133	130	127	124	124	121	117
	3	275	220	193	179	165	157	149	143	138	132	129	124	121	118	116	113	110	110	107	105
185	2	353	282	247	229	212	201	191	184	177	169	166	159	155	152	148	145	141	141	138	134
	3	314	251	220	204	188	179	170	163	157	151	148	141	138	135	132	129	126	126	122	119
240	2	415	332	291	270	249	237	224	216	208	199	195	187	183	178	174	170	166	166	162	158
	3	369	295	258	240	221	210	199	192	185	177	173	166	162	159	155	151	148	148	144	140

Tabella 6.B - Cavi multipolari in PVC posati in tubo o in canale (Tipi di posa di cui alla tab. 2.B)

Sezione [mm ²]	Numero cond. cavi	PORTATA (A)																			
		Numero di cavi multipolari																			
		1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1,5	2	16,5	13	11,5	10,5	10	9,5	9	8,5	8,5	8	8	7,5	7,5	7	7	7	6,5	6,5	6,5	6,5
	3	15	12	10,5	10	9	8,5	8	8	7,5	7	7	6,5	6,5	6,5	6,5	6	6	6	6	5,5
2,5	2	23	18,5	16	15	14	13	12,5	12	11,5	11	11	10,5	10	10	9,5	9,5	9	9	9	8,5
	3	20	16	14	13	12	11,5	11	10,5	10	9,5	9,5	9	9	8,5	8,5	8	8	8	8	7,5
4	2	30	24	21	19,5	18	17	16	15,5	15	14,5	14	13,5	13	13	12,5	12,5	12	12	11,5	11,5
	3	27	22	19	17,5	16	15,5	14,5	14	13,5	13	12,5	12	12	11,5	11,5	11	11	11	10,5	10,5
6	2	38	30	27	25	23	22	21	20	19	18	18	17	16,5	16,5	16	15,5	15	15	15	14,5
	3	34	27	24	22	20	19,5	18,5	17,5	17	16,5	16	15,5	15	14,5	14,5	14	13,5	13,5	13,5	13
10	2	52	42	36	34	31	30	28	27	26	25	24	23	23	22	22	21	21	21	20	20
	3	46	37	32	30	28	26	25	24	23	22	22	21	20	20	19,5	19	18,5	18,5	18	17,5
16	2	69	56	48	45	41	39	37	36	35	33	32	31	30	30	29	28	28	28	27	26
	3	62	50	43	40	37	35	33	32	31	30	29	28	27	27	26	25	25	25	24	24
25	2	90	72	63	59	54	51	49	47	45	43	42	41	40	39	38	37	36	36	35	34
	3	80	64	56	52	48	46	43	42	40	38	38	36	35	34	34	33	32	32	31	30
35	2	111	89	78	72	67	63	60	58	56	53	52	50	49	48	47	46	44	44	43	42
	3	99	79	69	64	59	56	53	51	50	48	47	45	44	43	42	41	40	40	39	38
50	2	133	106	93	86	80	76	72	69	67	64	63	60	59	57	56	55	53	53	52	51
	3	118	94	83	77	71	67	64	61	59	57	55	53	52	51	50	48	47	47	46	45
70	2	168	134	118	109	101	96	91	87	84	81	79	76	74	72	71	69	67	67	66	64
	3	149	119	104	97	89	85	80	77	75	72	70	67	66	64	63	61	60	60	58	57
95	2	201	161	141	131	121	115	109	105	101	96	94	90	88	86	84	82	80	80	78	76
	3	179	143	125	116	107	102	97	93	90	86	84	81	79	77	75	73	72	72	70	68
120	2	232	186	162	151	139	132	125	121	116	111	109	104	102	100	97	95	93	93	90	88
	3	206	165	144	134	124	117	111	107	103	99	97	93	91	89	87	84	82	82	80	78
150	2	259	206	181	168	155	147	139	134	129	124	121	116	114	111	108	106	103	103	101	98
	3	225	180	158	146	135	128	122	117	113	108	106	101	99	97	95	92	90	90	88	86
185	2	294	235	206	191	176	168	159	153	147	141	138	132	129	126	123	121	118	118	115	112
	3	255	204	179	166	153	145	138	133	128	122	120	115	112	110	107	105	102	102	99	97
240	2	344	275	241	224	206	196	186	179	172	165	162	155	151	148	144	141	138	138	134	131
	3	297	238	208	193	178	169	160	154	149	143	140	134	131	128	125	122	119	119	116	113
300	2	394	315	276	256	236	225	213	205	197	189	185	177	173	169	165	162	158	158	154	150
	3	339	271	237	220	203	193	183	176	170	163	159	153	149	146	142	139	136	136	132	129

Tabella 6.C - Cavi multipolari in PVC posati in fascio su passerelle perforate o mensole

Sezione [mm ²]	Numero cond. caricati	PORTATA (A)																			
		Numero di cavi multipolari																			
		1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1.5	2	22	17,5	15,5	14,5	13	12,5	12	11,5	11	10,5	10,5	10	9,5	9,5	9	9	9	9	8,5	8,5
	3	18,5	15	13	12	11	10,5	10	9,5	9,5	9	8,5	8,5	8	8	8	7,5	7,5	7,5	7	7
2.5	2	30	24	21	19,5	18	17	16	15,5	15	14,5	14	13,5	13	13	12,5	12,5	12	12	11,5	11,5
	3	25	20	17,5	16,5	15	14,5	13,5	13	12,5	12	12	11,5	11	11	10,5	10,5	10	10	10	9,5
4	2	40	32	28	26	24	23	22	21	20	19	19	18	17,5	17	17	16,5	16	16	15,5	15
	3	34	27	24	22	20	19,5	18,5	17,5	17	16,5	16	15,5	15	14,5	14,5	14	13,5	13,5	13,5	13
6	2	51	41	36	33	31	29	28	27	26	24	24	23	22	22	21	21	20	20	20	19,5
	3	43	34	30	28	26	25	23	22	22	21	20	19,5	19	18,5	18	17,5	17	17	17	16,5
10	2	70	56	49	46	42	40	38	36	35	34	33	32	31	30	29	29	28	28	27	27
	3	60	48	42	39	36	34	32	31	30	29	28	27	26	26	25	25	24	24	23	23
16	2	94	75	66	61	56	54	51	49	47	45	44	42	41	40	39	39	38	38	37	36
	3	80	64	56	52	48	46	43	42	40	38	38	36	35	34	34	33	32	32	31	30
25	2	119	95	83	77	71	68	64	62	60	57	56	54	52	51	50	49	48	48	46	45
	3	101	81	71	66	61	58	55	53	51	48	47	45	44	43	42	41	40	40	39	38
35	2	148	118	104	96	89	84	80	77	74	71	70	67	65	64	62	61	59	59	58	56
	3	126	101	88	82	76	72	68	66	63	60	59	57	55	54	53	52	50	50	49	48
50	2	180	144	126	117	108	103	97	94	90	86	85	81	79	77	76	74	72	72	70	68
	3	153	122	107	99	92	87	83	80	77	73	72	69	67	66	64	63	61	61	60	58
70	2	232	186	162	151	139	132	125	121	116	111	109	104	102	100	97	95	93	93	90	88
	3	196	157	137	127	118	112	106	102	98	94	92	88	86	84	82	80	78	78	76	74
95	2	282	226	197	183	169	161	152	147	141	135	133	127	124	121	118	116	113	113	110	107
	3	238	190	167	155	143	136	129	124	119	114	112	107	105	102	100	98	95	95	93	90
120	2	328	262	230	213	197	187	177	171	164	157	154	148	144	141	138	134	131	131	128	125
	3	276	221	193	179	166	157	149	144	138	132	130	124	121	119	116	113	110	110	108	105
150	2	379	303	265	246	227	216	205	197	190	182	178	171	167	163	159	155	152	152	148	144
	3	319	255	223	207	191	182	172	166	160	153	150	144	140	137	134	131	128	128	124	121
185	2	434	347	304	282	260	247	234	226	217	208	204	195	191	187	182	178	174	174	169	165
	3	364	291	255	237	218	207	197	189	182	175	171	164	160	157	153	149	146	146	142	138
240	2	514	411	360	334	308	293	278	267	257	247	242	231	226	221	216	211	206	206	200	195
	3	430	344	301	280	258	245	232	224	215	206	202	194	189	185	181	176	172	172	168	163
300	2	593	474	415	385	356	339	320	308	297	285	279	267	261	255	249	243	237	237	231	225
	3	497	398	348	323	298	283	268	258	249	239	234	224	219	214	209	204	199	199	194	189

Tabella 6.D - Cavi multipolari in PVC posati in strato, su passerelle perforate.

Sezione [mm ²]	Numero cond. caricati	PORTATA (A)								
		Numero di cavi multipolari								
		1	2	3	4	5	6	7	8	9
1.5	2	22	19,5	18	17	16,5	16	16	16	16
	3	18,5	16,5	15	14	14	13,5	13,5	13,5	13,5
2.5	2	30	26	25	23	23	22	22	22	22
	3	25	22	21	19,5	19	18,5	18,5	18	18
4	2	40	35	33	31	30	29	29	29	29
	3	34	30	28	26	26	25	25	24	24
6	2	51	45	42	39	38	37	37	37	37
	3	43	38	35	33	32	31	31	31	31
10	2	70	62	57	54	53	51	51	50	50
	3	60	53	49	46	45	44	44	43	43
16	2	94	83	77	72	71	69	69	68	68
	3	80	70	66	62	60	58	58	58	58
25	2	119	105	98	92	89	87	87	86	86
	3	101	89	83	78	76	74	74	73	73
35	2	148	130	121	114	111	108	108	107	107
	3	126	111	103	97	95	92	92	91	91
50	2	180	158	148	139	135	131	131	130	130
	3	153	135	125	118	115	112	112	110	110
70	2	232	204	190	179	174	169	169	167	167
	3	196	172	161	151	147	143	143	141	141
95	2	282	248	231	217	212	206	206	203	203
	3	238	209	195	183	179	174	174	171	171
120	2	328	280	269	253	246	239	239	236	236
	3	276	243	226	213	207	201	201	199	199
150	2	379	334	311	292	284	277	277	273	273
	3	319	281	262	246	239	233	233	230	230
185	2	434	382	356	334	326	317	317	312	312
	3	364	320	298	280	273	266	266	262	262
240	2	514	452	421	396	386	375	375	370	370
	3	430	378	353	331	323	314	314	310	310
300	2	593	522	486	457	445	433	433	427	427
	3	497	437	408	383	373	363	363	358	358

Tabella 6.E - Cavi multipolari in PVC posati in strato, su mensole

Sezione [mm ²]	Numero cond. caricati	PORTATA (A)								
		Numero di cavi multipolari								
		1	2	3	4	5	6	7	8	9
1,5	2	22	19	18	17,5	17,5	17,5	17,5	17	17
	3	18,5	16	15	15	15	14,5	14,5	14,5	14,5
2,5	2	30	26	25	24	24	24	24	23	23
	3	25	22	21	20	20	20	20	19,5	19,5
4	2	40	35	33	32	32	32	32	31	31
	3	34	30	28	27	27	27	27	27	27
6	2	51	44	42	41	41	40	40	40	40
	3	43	37	35	34	34	34	34	34	34
10	2	70	61	57	56	56	55	55	55	55
	3	60	52	49	48	48	47	47	47	47
16	2	94	82	77	75	75	74	74	73	73
	3	80	70	66	64	64	63	63	62	62
25	2	119	104	98	95	95	94	94	93	93
	3	101	88	83	81	81	80	80	79	79
35	2	148	129	121	118	118	117	117	115	115
	3	126	110	103	101	101	100	100	98	98
50	2	180	157	148	144	144	142	142	140	140
	3	153	133	125	122	122	121	121	119	119
70	2	232	202	190	186	186	183	183	181	181
	3	196	171	161	157	157	155	155	153	153
95	2	282	245	231	226	226	223	223	220	220
	3	238	207	195	190	190	188	188	186	186
120	2	328	285	269	262	262	259	259	256	256
	3	276	240	226	221	221	218	218	215	215
150	2	379	330	311	303	303	299	299	296	296
	3	319	278	262	255	255	252	252	249	249
185	2	434	378	356	347	347	343	343	339	339
	3	364	317	298	291	291	288	288	284	284
240	2	514	447	421	411	411	406	406	401	401
	3	430	374	353	344	344	340	340	335	335
300	2	593	516	486	474	474	468	468	463	463
	3	497	432	408	398	398	393	393	388	388

Tabella 6 F - Cavi unipolari senza guaina in EPR posati in tubo o in canale (Tipi di posa di cui alla tab. 2 A).

Sezione (mm²)	Numero cond. cavi	PORTATA (A)																			
		Numero di circuiti																			
		1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1.5	2	23	18.5	16	15	14	13	12.5	12	11.5	11	11	10.5	10	10	9.5	9.5	9	9	9	8.5
	3	20	16	14	13	12	11.5	11	10.5	10	9.5	9.5	9	9	8.5	8.5	8	8	8	7.5	
2.5	2	31	25	22	20	18.5	17.5	16.5	16	15.5	15	14.5	14	13.5	13.5	13	12.5	12.5	12	12	
	3	28	22	19.5	18	17	16	15	14.5	14	13.5	13	12.5	12.5	12	12	11.5	11	11	10.5	
4	2	42	34	29	27	25	24	23	22	21	20	19.5	19	18.5	18	17.5	17	17	17	16.5	
	3	37	30	26	24	22	21	20	19	18.5	18	17.5	16.5	16.5	16	15.5	15	15	15	14.5	
6	2	54	43	38	35	32	31	29	28	27	26	25	24	24	23	23	22	22	22	21	
	3	48	38	34	31	29	27	26	25	24	23	23	22	21	21	20	19.5	19	19	18.5	
10	2	75	60	53	49	45	43	41	39	38	36	35	34	33	32	32	31	30	30	29	
	3	66	53	46	43	40	38	36	34	33	32	31	30	29	28	28	27	26	26	25	
16	2	100	80	70	65	60	57	54	52	50	48	47	45	44	43	42	41	40	39	38	
	3	88	70	62	57	53	50	48	46	44	42	41	40	39	38	37	36	35	35	34	
25	2	133	106	93	86	80	76	72	69	67	64	63	60	59	57	56	55	53	52	51	
	3	117	94	82	76	70	67	63	61	59	56	55	53	51	50	49	48	47	46	44	
35	2	164	131	115	107	98	93	89	85	82	79	77	74	72	71	69	67	66	64	62	
	3	144	113	101	94	86	82	78	75	72	69	68	65	63	62	60	59	58	56	55	
50	2	198	158	139	129	119	113	107	103	99	95	93	89	87	85	83	81	79	77	75	
	3	175	140	123	114	105	100	95	91	88	84	82	79	77	75	74	72	70	68	67	
70	2	253	202	177	164	152	144	137	132	127	121	119	114	111	109	106	104	101	99	96	
	3	222	178	155	144	133	127	120	115	107	104	100	98	95	93	91	89	87	84	81	
95	2	306	245	214	199	184	174	165	159	153	147	144	138	135	132	129	125	122	119	116	
	3	269	215	188	175	161	153	145	140	135	129	126	121	118	116	113	110	108	105	102	
120	2	354	283	248	230	212	202	191	184	177	170	166	159	156	152	149	145	142	138	135	
	3	312	250	218	203	187	178	168	162	156	150	147	140	137	134	131	128	125	122	119	
150	2	402	322	281	261	241	229	217	209	201	193	189	181	177	173	169	165	161	157	153	
	3	355	284	249	231	213	202	192	185	178	170	167	160	156	153	149	146	142	138	135	
185	2	472	378	330	307	283	269	255	245	236	227	222	212	208	203	198	194	189	184	179	
	3	417	334	292	271	250	238	225	217	209	200	196	188	183	179	175	171	167	163	158	
240	2	555	444	389	361	333	316	300	289	278	266	261	250	244	239	233	228	222	216	211	
	3	490	392	343	319	294	279	265	255	245	235	230	221	216	211	206	201	196	191	186	

Tabella 6 G - Cavi multipolari in EPR posati in tubo o in canale (Tipi di posa di cui alla tab. 2 B).

Sezione (mm²)	Numero cond. cavi	PORTATA (A)																			
		Numero di cavi multipolari																			
		1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1.5	2	22	17.5	15.5	14.5	13	12.5	12	11.5	11	10.5	10.5	10	9.5	9.5	9	9	9	9	8.5	8.5
	3	19.5	15.5	13.5	12.5	11.5	11	10.5	10	10	9.5	9	9	8.5	8.5	8	8	8	8	7.5	7.5
2.5	2	30	24	21	19.5	18	17	16	15.5	15	14.5	14	13.5	13	13	12.5	12.5	12	12	11.5	11.5
	3	26	21	18	17	15.5	15	14	13.5	13	12.5	12	11.5	11.5	11	11	10.5	10.5	10	10	10
4	2	40	32	28	26	24	23	22	21	20	19	19	18	17.5	17	17	16.5	16	16	15.5	15
	3	35	28	25	23	21	20	19	18	17.5	17	16.5	16	15.5	15	14.5	14.5	14	14	13.5	13.5
6	2	51	41	36	33	31	29	28	27	26	24	24	23	22	22	21	21	20	20	19.5	19.5
	3	44	35	31	29	26	25	24	23	22	21	21	20	19.5	19	18.5	18	17.5	17	16.5	16.5
10	2	69	55	48	45	41	39	37	36	35	33	32	31	30	30	29	28	28	27	26	26
	3	60	48	42	39	36	34	32	31	30	29	28	27	26	26	25	25	24	24	23	23
16	2	91	73	64	59	55	52	49	47	46	44	43	41	40	39	38	37	36	36	35	35
	3	80	64	56	52	48	46	43	42	40	38	38	36	35	34	34	33	32	32	31	30
25	2	119	95	83	77	71	68	64	62	60	57	56	54	52	51	50	49	48	46	45	45
	3	105	84	74	68	63	60	57	55	53	50	49	47	46	45	44	43	42	41	40	40
35	2	146	117	102	95	88	83	79	76	73	70	69	66	64	63	61	60	58	57	55	55
	3	128	102	90	83	77	73	69	67	64	61	60	58	56	55	54	52	51	51	50	49
50	2	175	140	123	114	105	100	95	91	88	84	82	79	77	75	74	72	70	68	67	67
	3	154	123	108	100	92	88	83	80	77	74	72	69	68	66	65	63	62	62	60	59
70	2	221	177	155	144	133	126	119	115	111	106	104	99	97	95	93	91	88	86	84	84
	3	194	155	136	126	116	111	105	101	97	93	91	87	85	83	81	80	78	76	74	74
95	2	265	212	186	172	159	151	143	138	133	127	125	119	117	114	111	109	106	103	101	101
	3	233	186	163	151	140	133	126	121	117	112	110	105	103	100	98	96	93	91	89	89
120	2	305	244	214	199	183	174	165	159	153	146	143	137	134	131	128	125	122	119	116	116
	3	262	214	188	174	161	153	145	139	134	129	126	121	118	115	113	110	107	105	102	102
150	2	334	267	234	217	200	190	180	174	167	160	157	150	147	144	140	137	134	130	127	127
	3	300	240	210	195	180	171	162	156	150	144	141	135	132	129	126	123	120	117	114	114
185	2	384	307	269	250	230	219	207	200	192	184	180	173	169	165	161	157	154	150	146	146
	3	340	272	238	221	204	194	184	177	170	163	160	153	150	146	143	139	136	133	129	129
240	2	459	367	321	298	275	262	248	239	230	220	216	207	202	197	193	188	184	179	174	174
	3	398	318	279	259	239	227	215	207	199	191	187	179	175	171	167	163	159	155	151	151
300	2	532	426	372	346	319	303	287	277	266	255	250	239	234	229	223	218	213	207	202	202
	3	455	364	319	296	273	259	246	237	228	218	214	205	200	196	191	187	182	177	173	173

Tabella 6 H - Cavi multipolari in EPR posati in fascio, su passerelle perforate o mensole.

Sezione [mm ²]	Numero cond. caricati	PORTATA (A)																			
		Numero di cavi multipolari																			
		1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1,5	2	26	21	18	17	15,5	15	14	13,5	13	12,5	12	11,5	11,5	11	11	10,5	10,5	10,5	10	10
	3	23	18,5	16	15	14	13	12,5	12	11,5	11	11	10,5	10	10	9,5	9,5	9	9	9	9
2,5	2	36	29	25	24	22	21	19,5	18,5	18	17,5	17	16	16	15,5	15	15	14,5	14,5	14	13,5
	3	32	26	22	21	19	18	17,5	16,5	16	15,5	15	14,5	14	14	13,5	13	13	13	12,5	12
4	2	49	39	34	32	29	28	26	25	25	24	23	22	22	21	21	20	19,5	19,5	19	18,5
	3	42	34	29	27	25	24	23	22	21	20	20	19	18,5	18	17,5	17	17	16,5	16	16
6	2	63	50	44	41	38	36	34	33	32	31	30	28	28	27	26	26	25	25	24	24
	3	54	43	38	35	32	31	29	28	27	26	25	24	24	23	23	22	22	21	21	21
10	2	86	69	60	56	52	49	46	45	43	41	40	39	38	37	36	35	34	34	34	33
	3	75	60	53	49	45	43	41	39	38	36	35	34	33	32	31	30	30	29	29	29
16	2	115	92	81	75	69	66	62	60	58	56	54	52	51	49	48	47	46	46	45	44
	3	100	80	70	65	60	57	54	52	50	48	47	45	44	43	42	41	40	40	39	38
25	2	149	119	104	97	89	85	80	77	75	72	70	67	66	64	63	61	60	60	58	57
	3	127	102	89	83	76	72	69	66	64	61	60	57	56	55	53	52	51	51	50	48
35	2	185	148	130	120	111	105	100	96	93	89	87	83	81	80	78	76	74	74	72	70
	3	158	126	111	103	95	90	85	82	79	76	74	71	70	68	66	65	63	63	62	60
50	2	225	180	158	146	135	128	122	117	113	108	106	101	99	97	95	92	90	90	88	86
	3	192	154	134	125	115	108	104	100	96	92	90	86	84	83	81	79	77	77	75	73
70	2	289	231	202	188	173	165	156	150	145	139	136	130	127	124	121	118	116	116	113	110
	3	246	197	172	160	148	140	133	128	123	118	116	111	108	106	103	101	98	98	96	93
95	2	352	282	246	229	211	201	190	183	176	169	165	158	155	151	148	144	141	141	137	134
	3	298	238	209	194	179	170	161	155	149	143	140	134	131	128	125	122	119	119	116	113
120	2	410	328	287	267	246	234	221	213	205	197	193	185	180	176	172	168	164	164	160	156
	3	346	277	242	225	208	197	187	180	173	166	163	156	152	149	145	142	138	138	135	131
150	2	473	378	331	307	284	270	255	246	237	227	222	213	208	203	199	194	189	189	184	180
	3	399	319	279	259	239	227	215	207	200	192	188	180	176	172	168	164	160	160	156	152
185	2	542	434	379	352	325	309	293	282	271	260	255	244	238	233	228	222	217	217	211	206
	3	456	365	319	296	274	260	246	237	228	219	214	205	201	196	192	187	182	182	178	173
240	2	641	513	449	417	385	365	346	333	321	308	301	288	282	276	269	263	256	256	244	240
	3	538	430	377	350	323	307	291	280	269	258	253	242	237	231	226	221	215	215	210	204
300	2	741	593	519	482	445	422	400	385	371	356	348	333	326	319	311	304	296	296	289	282
	3	621	497	435	404	373	354	335	323	311	298	292	279	273	267	261	255	248	248	242	236

Tabella 6 I - Cavi multipolari in EPR posati in strato, su passerelle perforate.

Sezione [mm ²]	Numero cond. caricati	PORTATA (A)								
		Numero di cavi multipolari								
		1	2	3	4	5	6	7	8	9
1,5	2	26	23	21	20	19,5	19	19	18,5	18,5
	3	23	20	19	17,5	17,5	17	17	16,5	16,5
2,5	2	36	32	30	28	27	26	26	26	26
	3	32	28	26	25	24	23	23	23	23
4	2	49	43	40	38	37	36	36	35	35
	3	42	37	34	32	32	31	31	30	30
6	2	63	55	52	49	47	46	46	45	45
	3	54	48	44	42	41	39	39	39	39
10	2	86	76	71	66	65	63	63	62	62
	3	75	66	62	58	56	55	55	54	54
16	2	115	101	94	89	86	84	84	83	83
	3	100	88	82	77	75	73	73	72	72
25	2	149	131	122	115	112	108	109	107	107
	3	127	112	104	98	95	93	93	91	91
35	2	185	163	152	142	139	135	135	133	133
	3	158	139	130	122	119	115	115	114	114
50	2	225	198	185	173	169	164	164	162	162
	3	192	169	157	148	144	140	140	138	138
70	2	289	254	237	223	217	211	211	208	208
	3	246	216	202	189	185	180	180	177	177
95	2	352	310	289	271	264	257	257	253	253
	3	298	262	244	229	224	218	218	215	215
120	2	410	361	336	316	308	299	299	295	295
	3	346	304	284	266	260	253	253	249	249
150	2	473	416	388	364	355	345	345	341	341
	3	399	351	327	307	299	291	291	287	287
185	2	542	477	444	417	407	396	396	390	390
	3	456	401	374	351	342	333	333	328	328
240	2	641	564	526	494	481	466	466	462	462
	3	538	473	441	414	404	393	393	387	387
300	2	741	652	608	571	556	541	541	534	534
	3	621	546	509	478	466	453	453	447	447

Tabella 6 L - Cavi multipolari in EPR posati in strato, su mensole.

Sezione [mm ²]	Numero cond. caricati	PORTATA (A)								
		Numero di cavi multipolari								
		1	2	3	4	5	6	7	8	9
1,5	2	26	23	21	21	21	21	21	20	20
	3	23	20	19	18,5	18,5	18	18	18	18
2,5	2	36	31	30	29	29	28	28	28	28
	3	32	28	26	26	26	25	25	25	25
4	2	49	43	40	39	39	39	39	38	38
	3	42	37	34	34	34	33	33	33	33
6	2	63	55	52	50	50	50	50	49	49
	3	54	47	44	43	43	43	43	42	42
10	2	86	75	71	69	69	68	68	67	67
	3	75	65	62	60	60	59	59	59	59
16	2	115	100	94	92	92	91	91	90	90
	3	100	87	82	80	80	79	79	78	78
25	2	149	130	122	119	119	118	118	116	116
	3	127	110	104	102	102	100	100	99	99
35	2	185	161	152	148	148	146	146	144	144
	3	158	137	130	126	126	125	125	123	123
50	2	225	196	185	180	180	178	178	176	176
	3	192	167	157	154	154	152	152	150	150
70	2	289	251	237	231	231	228	228	225	225
	3	246	214	202	197	197	194	194	192	192
95	2	352	306	289	282	282	278	278	275	275
	3	298	259	244	238	238	235	235	232	232
120	2	410	357	336	328	328	324	324	320	320
	3	346	301	284	277	277	273	273	270	270
150	2	473	412	388	378	378	374	374	369	369
	3	399	347	327	319	319	315	315	311	311
185	2	542	472	444	434	434	428	428	423	423
	3	456	397	374	365	365	360	360	356	356
240	2	641	558	526	513	513	506	506	500	500
	3	538	468	441	430	430	425	425	420	420
300	2	741	645	608	593	593	585	585	578	578
	3	621	540	509	497	497	491	491	484	484